



TerraWave Solutions® 380-960 MHz 2-Way Cavity Splitter with N-Style Jack Connector

TerraWave’s antenna splitters are designed to divide or “split” the RF signal from one radio to multiple antennas. The splitters are perfect for applications that require coverage of two different areas with a single access point or bridge. TerraWave’s splitters are designed for the 380-960 MHz marketplace. The units’ rugged design and small footprint make them ideal for most bridging and LAN applications. Every TerraWave splitter is covered by the Company’s one-year warranty program. For questions and to purchase product, contact a wireless networking regional account executive at 210-375-8482, 800-851-4965 or sales@terrawave.com. Visit www.terrawave.com for additional information.

Features and Benefits:

- Provide RF coverage in separate areas with a single access point or bridge
- Compact, lightweight design
- Easy to mount
- High isolation, low insertion loss and minimal VSWR
- N-Style Jack connector included
- Excellent value - Superior performance at a competitive price



Specifications

Model	RMFLT-2-M2-NJ-CAV
Frequency Range	380 ~ 960 MHz
Splitting Power	50:50
Insertion Loss	≤ 3.2 dB
VSWR	≤1.2
Impedance	50 Ω
Maximum Power	300 Watts
Connector	N-Style Jack
Operating Temperature Range	-22°F to +140°F
Humidity	5 % ~ 95 %
Dimensions	9.4” x 2.6” x 1.1”
Weight	10.2 ounces
Dimensions	12.99” x 1.89” x 1.14”
Weight	11.5 ounces
Ingress Protection Rating	IP53