

TerraWave Solutions® 2.4 GHz 2-Way Splitter with N-Style Jack Connector

TerraWave’s antenna splitters are designed to divide or “split” the RF signal from one radio to multiple antennas. The splitters are perfect for applications that require coverage of two different areas with a single access point or bridge. The units’ rugged design and small footprint make them ideal for most outdoor bridging and WLAN applications. Each splitter includes a one-year warranty. Visit www.terrawave.com for additional information.

Note: Requires two splitters per AP when using diversity

Features and Benefits:

- Provide RF coverage in separate areas with a single access point or bridge
- Compact, lightweight design
- Easy to mount
- High isolation, low insertion loss and minimal VSWR
- N-Style Jack connector included
- Excellent value - Superior performance at a competitive price



Specifications

Model	RMFLT-2-2400N
Frequency Range	1700 - 2500 MHz
Insertion Loss	≤ 3.5 dB
Isolation	≥ 20 dB
VSWR	≤1.4
Impedance	50 Ω
Maximum Power	50 Watts
Connector	N-Style Jack
Operating Temperature Range	-22°F to +140°F
Humidity	5 % – 95 %
Dimensions	4.6" x 3.3" x 0.8"
Weight	8.5 ounces